



MODULAR BATTERY CHARGER

for Dell Latitude Rugged Batteries

FEATURES

- Simultaneously charge Dell batteries for the 5420, 5424 and 7424 Dell Latitude Rugged Notebooks and 7202 and 7212 Tablets

TECHNICAL SPECIFICATIONS

- Input Voltage — 19.5 Vdc
- Max Current Charge: 1 Amp/bay (up to 10 Amps)
- Temperature Range = 32°F to 104°F (0°C to 40°C)
NOTE: Charging outside of temp range may result in temporary stoppage of charging.
- LED Light Indicator: Green / Yellow / Red
- Product Weight = 0.5 lbs
- Packaged Weight = 0.75 lbs
- Tested to MIL-STD-810G certification



Keep your Dell Latitude Rugged Batteries fully charged with the Lind Electronics Modular Multi Bay Charger. Charge up to 16 batteries per charger with interchangeable battery bays for the Dell Latitude Rugged line of notebook and tablet computers. Lind battery chargers incorporate the highest degree of circuit protection to ensure your Dell batteries are charged properly.

The Lind Electronics Modular Multi Bay Charger begins with the Master Controller (DECHMC-5021). This is powered by a single Dell compatible AC Power Adapter. The wattage of the AC Adapter can range from 45 to 330 watts and will determine how many batteries are charged simultaneously. The higher the wattage of the AC Adapter, the higher the number of batteries being charged, lowering the overall charge time. The power adapter shipped with the Dell Latitude Rugged Notebook or Tablet may be used with the charging system. When charging four batteries or more, a 240 watt adapter is recommended for optimal charging times. Connected to the Master Controller are the individual battery Charger Bays.

The DECHCB-5022 bay charges batteries for the Dell Latitude Rugged 5420, 5424 and 7424 Notebooks. The DECHCB-5023 bay charges batteries for the Dell Latitude Rugged 7202 and 7212 Tablets. Any combination of bays (up to 16) may be used within the same charging system.

The Lind Electronics Modular Multi Bay Charger can support the charging for as little as 1 bay all the way up to 16 bays per Master Charger.

For more information on our battery chargers or any of our other products, please visit us at www.lindelectronics.com.

U.S. OFFICE

14850 Deveau Place
Minnetonka, MN 55345
1-952-927-6303
info@lindelectronics.com

EUROPEAN OFFICE

Gotthard-Mueller-Str. 5
70794 Filderstadt, Germany
+49 711 7070 7308
+49 152 0856 1191 (mobile)
meisele@lindelectronics.com